## Exam Theory of Automata and Processes (2IT15)

6 August 2008, 9.00 –12.00

Faculteit Wiskunde en Informatica Technische Universiteit Eindhoven (TU/e)

This is a "closed book" exam. The parts add up to 100 points, the grade is obtained by dividing the total number of points by 10. *Motivate your answers!* 

**Assignment 1** . Given is the following recursive specification:

$$\begin{array}{cccc} S & \leftrightarrows & 1+a.T+a.U \\ T & \leftrightarrows & \tau.V \\ U & \leftrightarrows & 1+b.V \\ V & \leftrightarrows & b.U \end{array}$$

Give the non-deterministic automaton for S given by the operational rules. Next, find a deterministic automaton without  $\tau$ -steps that accepts the same language as the automaton of S. Finally, give an iteration expression for this language. (20 points)

 $\bf Assignment~2$  . Construct a pushdown automaton that accepts the following language:

$$L = \{a^n b^{2n} \mid n \ge 0\}.$$

(17 points)

 ${\bf Assignment~3}$  . Construct a Turing machine that accepts the following language:

$$L = \{a^{2n}b^n \mid n \ge 0\}.$$

(17 points)

**Assignment 4**. Consider the language  $L = \{a^n b^m a^n \mid n, m \geq 0\}$ . Show by using the pumping lemma that this language is not regular. (20 points)

**Assignment 5** We consider two buffers, where messages along the connecting port may yield an error  $\bot$ . See the picture.

Take the data set  $D = \{0, 1\}$ . The buffers B and C are given by:

$$B = ?_{1}0.B_{0} + ?_{1}1.B_{1}$$

$$B_{d} = \tau .!_{2}d.B + \tau .!_{2} \bot .B_{d} \quad \text{(for } d = 0, 1\text{)}$$

$$C = ?_{2} \bot .C + ?_{2}0.!_{3}0.C + ?_{2}1.!_{3}1.C.$$

- a. Derive a recursive specification for the process  $\partial_2(B||C)$ , and draw a transition system.
- b. Consider the process  $\tau_2(\partial_2(B||C))$ . Find a transition system without  $\tau$ steps, that is branching bisimilar to this process. Notice that this process
  is equal to a two place buffer, which means this is a correct communication
  protocol.
- c. Why does the equation of  $B_d$  contain  $\tau$ 's? What can happen if they are omitted?
- d. How can the system behave correctly, without the need for an acknowledgement going back (from C to B)?

(26 points)